



## HRX 5000

Call: 01623 883 073

## HRX 5000

### RFID Proximity Fob | Card Terminal

In addition to the Time and Attendance features of our 3000 model, the 5000 also handles access control and bells (such as factory bells announcing breaks). This means that authorised personnel can use their proximity cards for both clocking IN/OUT and gaining access to protected areas of the building. The access control features include built in hardware to control two doors, relay output, door ajar alarm and a door exit timer.

## Features

- 2 Modes of operation - Intelligent and non intelligent suitable for single or multi-site operation.
- Built-in hardware to control 2 doors
- Relay output
- Remote proximity reader output
- High throughput of employees during busy periods
- Capacity upgrades available as business demands change
- Access Control - Define multiple access patterns
- RFID contact-less readers that require no maintenance
- Robust ABS plastic casing suitable for use with external enclosures for outdoor use
- Fire Alarm trigger built in - triggers when fire alarm is sounded, sending message to either a connected or network printer. Advising who is onsite.



Size (W) x (H) x (D)	280mm (W) x 170mm (H) x 60mm (D)
LCD Screen	16 x 2 LCD/LED black light display 100mm x 25mm display area
Power	12V DC, 54 watts, 50/60Hz 3 year lithium battery backup
Enclosure	Flame retardants ABS
Battery Life	Up to 3 years via the standard internal lithium battery
Number of Clocking	8,000 in circular buffer
Proximity Options	Mifare - card/FOB
User Capacity	Employees - 25 - 1000 (upgrades available)
PC Communications	RS232 and a TCP/IP 1x Fire alarm input trigger
Terminal Communications	TCP/IP between terminals (Slave terminals)
Firmware	Flash memory upgradeable over TCP/IP
Operation Modes	Non/Intelligent
Optional Extra	Keypad with extra functions